

MLFB-Ordering data

6SL3210-5BB17-5BV1



Figure similar

| Client order no. : |
|--------------------|
| Order no. : |
| Offer no. : |
| Remarks : |

| item no. : | |
|-----------------|---|
| Consignment no. | : |
| Project : | |

| Rated data | | General tee | General tech. specifications | |
|--------------------|-----------------------|---------------------------|--|--|
| Input | | Power factor λ | 0.72 | |
| Number of phases | 1 AC | Offset factor $\cos \phi$ | 0.95 | |
| Line voltage | 200 240 V -15 % +10 % | Efficiency η | 0.98 | |
| Line frequency | 47 63 Hz | Ambient conditions | | |
| Output | | Cooling | convection cooling | |
| Number of phases | 3 AC | Installation altitude | 1000 m (3281 ft) | |
| Rated voltage | 230 V | Ambient temperature | | |
| Rated power (HO) | 0.75 kW / 1.00 hp | Operation | -10 60 °C (14 140 °F) | |
| Rated power (LO) | 0.75 kW / 0.75 hp | Storage | -40 70 °C (-40 158 °F) | |
| Rated current (HO) | 4.20 A | Relative humidity | | |
| Rated current (LO) | 4.20 A | Max. operation | 95 % | |
| | | Communication | | |
| | | Communication | USS, Modbus RTU | |
| Pulse frequency | 8.00 kHz | Standards | | |
| Output frequency | 0 550 Hz | Compliance with standards | CE, cULus, C-Tick (RCM), KC | |
| | | CE marking | EN 61800-5-1 /EN 60204-1 and EN 61800-3 | |

Overload capability

Low Overload (LO)

110 % rated output current for 60 s, cycle time 300 s

High Overload (HO)

150 % rated output current for 60 s, cycle time 300 s



MLFB-Ordering data

6SL3210-5BB17-5BV1



Figure similar

| Mechanical data | | Connections | |
|---|---|----------------------|---------------|
| Mounting position Wall mounting / side-by-side mounting | | Max. motor cable len | gth |
| | founding , side by side mounting | Shielded | 25 m (82 ft) |
| Degree of protection IP20 / | UL open type | Unshielded | 50 m (164 ft) |
| Size FSAB | | | |
| Net weight 0.80 k | cg(1.76 lb) | | |
| Width 68.0 r | 68.0 mm (2.68 in) | | |
| Height 142.0 | mm (5.59 in) | | |
| Depth 127.8 | mm (5.03 in) | | |
| Inputs / outputs | | | |
| Standard digital inputs | | | |
| Number | 4 | | |
| Digital outputs | | | |
| Number as relay changeover contact | : 1 | | |
| Number as transistor | 1 | | |
| Analog inputs | | | |
| Number | 2 (Can be used as additional digital input) | | |
| Analog outputs | | | |
| Number | 1 | | |
| | | | |